

## 4-bit Single Chip Microcomputer



### DESCRIPTION


The E0C63458 is a microcomputer which has a high-performance 4-bit CPU E0C63000 as the core CPU, ROM (8,192 words  $\times$  13 bits), RAM (5,120 words  $\times$  4 bits), serial interface, watchdog timer, programmable timer, time base counters (2 systems), SVD circuit, a dot-matrix LCD driver that can drive a maximum 60 segments  $\times$  17 commons and sound generator built-in. The E0C63458 features high speed operation and low current consumption in a wide operating voltage range (2.2 V to 6.4 V), this makes it suitable for applications working with batteries. It is also suitable for caller ID and portable data bank systems because it has a large capacity of RAM built-in.

### FEATURES



- CMOS LSI 4-bit parallel processing
- OSC1 oscillation circuit ..... 32.768 kHz (Typ.) crystal or 60 kHz (Typ.) CR oscillation circuit (\*1)
- OSC3 oscillation circuit ..... 1.8 MHz (Typ.) CR or 4 MHz (Max.) ceramic oscillation circuit (\*1)
- Instruction set ..... Basic instruction: 46 types (411 instructions with all)  
Addressing mode: 8 types
- Instruction execution time ..... During operation at 32.768 kHz: 61  $\mu$ sec 122  $\mu$ sec 183  $\mu$ sec  
During operation at 60 kHz: 33  $\mu$ sec 67  $\mu$ sec 100  $\mu$ sec  
During operation at 4 MHz: 0.5  $\mu$ sec 1  $\mu$ sec 1.5  $\mu$ sec
- ROM capacity ..... Code ROM: 8,192 words  $\times$  13 bits  
Data ROM: 2,048 words  $\times$  4 bits (= 8K bits)
- RAM capacity ..... Data memory: 5,120 words  $\times$  4 bits  
Display memory: 1,020 bits (240 words  $\times$  4 bits + 60  $\times$  1 bit)
- Input port ..... 8 bits (Pull-up resistors may be supplemented \*1)
- Output port ..... 12 bits (It is possible to switch the 2 bits to special output \*2)
- I/O port ..... 12 bits (It is possible to switch the 2 bits to special output and the 4 bits to serial I/F input/output \*2)
- Serial interface ..... 1 port (8-bit clock synchronous system)
- LCD driver ..... 60 segments  $\times$  8, 16 or 17 commons (\*2)
- Time base counter ..... 2 systems (Clock timer, stopwatch timer)
- Programmable timer ..... Built-in, 2 inputs  $\times$  8 bits, with event counter function
- Watchdog timer ..... Built-in
- Sound generator ..... With envelope and 1-shot output functions
- Supply voltage detection (SVD) circuit .. 16 values, programmable (1.85 V to 3.30 V)  
(It is possible to switch 1 value to the external voltage detection \*1)
- External interrupt ..... Input port interrupt: 2 systems
- Internal interrupt ..... Clock timer interrupt: 4 systems  
Stopwatch timer interrupt: 2 systems  
Programmable timer interrupt: 2 systems  
Serial interface interrupt: 1 system

- Power supply voltage .....2.2 V to 6.4 V  
(Min. 1.8 V when the OSC3 oscillation circuit is not used)
  - Operating temperature range ..... -20°C to 70°C
  - Current consumption (Typ.) ..... Single clock (OSC1: Crystal oscillation):
    - During HALT (32 kHz)
      - 3.0 V (LCD power OFF) 1  $\mu$ A
      - 3.0 V (LCD power ON, Vc1 standard) 6  $\mu$ A
      - 3.0 V (LCD power ON, Vc2 standard) 4  $\mu$ A
    - During operation (32 kHz)
      - 3.0 V (LCD power ON, Vc1 standard) 10  $\mu$ A
  - ..... Twin clock:
    - During operation (4 MHz)
      - 3.0 V (LCD power ON, Vc1 standard) 1,000  $\mu$ A
  - Package ..... QFP8-144pin, QFP17-144pin, QFP5-128pin (plastic) or chip
- \*1: Can be selected with mask option \*2: Can be selected with software

■ BLOCK DIAGRAM



## ■ PIN CONFIGURATION



No.	Name	No.	Name	No.	Name	No.	Name
1	SEG13	37	N.C.	73	N.C.	109	N.C.
2	SEG12	38	N.C.	74	SVD	110	SEG47
3	SEG11	39	R23	75	Vc1	111	SEG46
4	SEG10	40	R22	76	Vc2	112	SEG45
5	SEG9	41	R21	77	Vc3	113	SEG44
6	SEG8	42	R20	78	Vc4	114	SEG43
7	SEG7	43	R13	79	Vc5	115	SEG42
8	SEG6	44	R12	80	CF	116	SEG41
9	SEG5	45	R11	81	CE	117	SEG40
10	SEG4	46	R10	82	CD	118	SEG39
11	SEG3	47	R03	83	CC	119	SEG38
12	SEG2	48	R02	84	CB	120	SEG37
13	SEG1	49	R01	85	CA	121	SEG36
14	SEG0	50	R00	86	COM8	122	SEG35
15	COM7	51	P23	87	COM9	123	SEG34
16	COM6	52	P22	88	COM10	124	SEG33
17	COM5	53	P21	89	COM11	125	SEG32
18	COM4	54	P20	90	COM12	126	SEG31
19	N.C.	55	P13	91	COM13	127	SEG30
20	COM3	56	P12	92	COM14	128	SEG29
21	COM2	57	P11	93	COM15	129	SEG28
22	COM1	58	P10	94	COM16	130	SEG27
23	COM0	59	P03	95	SEG59	131	SEG26
24	BZ	60	P02	96	SEG58	132	SEG25
25	Vss	61	P01	97	SEG57	133	SEG24
26	OSC1	62	P00	98	SEG56	134	SEG23
27	OSC2	63	K13	99	SEG55	135	SEG22
28	Vd1	64	K12	100	SEG54	136	SEG21
29	OSC3	65	K11	101	SEG53	137	SEG20
30	OSC4	66	K10	102	SEG52	138	SEG19
31	VDD	67	K03	103	SEG51	139	SEG18
32	RESET	68	K02	104	SEG50	140	SEG17
33	TEST	69	K01	105	SEG49	141	SEG16
34	VREF	70	K00	106	SEG48	142	SEG15
35	N.C.	71	N.C.	107	N.C.	143	SEG14
36	N.C.	72	N.C.	108	N.C.	144	N.C.

No.	Name	No.	Name	No.	Name	No.	Name
1	SEG49	33	SEG17	65	RESET	97	K02
2	SEG48	34	SEG16	66	TEST	98	K01
3	SEG47	35	SEG15	67	VREF	99	K00
4	SEG46	36	SEG14	68	N.C.	100	SVD
5	SEG45	37	SEG13	69	R23	101	Vc1
6	SEG44	38	SEG12	70	R22	102	Vc2
7	SEG43	39	SEG11	71	R21	103	Vc3
8	SEG42	40	SEG10	72	R20	104	Vc4
9	SEG41	41	SEG9	73	R13	105	Vc5
10	SEG40	42	SEG8	74	R12	106	CF
11	SEG39	43	SEG7	75	R11	107	CE
12	SEG38	44	SEG6	76	R10	108	CD
13	SEG37	45	SEG5	77	R03	109	CC
14	SEG36	46	SEG4	78	R02	110	CB
15	SEG35	47	SEG3	79	R01	111	CA
16	SEG34	48	SEG2	80	R00	112	COM8
17	SEG33	49	SEG1	81	P23	113	COM9
18	SEG32	50	SEG0	82	P22	114	COM10
19	SEG31	51	COM7	83	P21	115	COM11
20	SEG30	52	COM6	84	P20	116	COM12
21	SEG29	53	COM5	85	P13	117	COM13
22	SEG28	54	COM4	86	P12	118	COM14
23	SEG27	55	COM3	87	P11	119	SEG59
24	SEG26	56	COM2	88	P10	120	SEG58
25	SEG25	57	BZ	89	P03	121	SEG57
26	SEG24	58	Vss	90	P02	122	SEG56
27	SEG23	59	OSC1	91	P01	123	SEG55
28	SEG22	60	OSC2	92	P00	124	SEG54
29	SEG21	61	Vd1	93	K13	125	SEG53
30	SEG20	62	OSC3	94	K11	126	SEG52
31	SEG19	63	OSC4	95	K10	127	SEG51
32	SEG18	64	VDD	96	K03	128	SEG50

N.C. : No Connection

■ PIN DESCRIPTION

Pin name	Pin No.		In/Out	Function
	QFP8-144, QFP17-144	QFP5-128		
V <sub>DD</sub>	31	64	–	Power (+) supply pin
V <sub>SS</sub>	25	58	–	Power (–) supply pin
V <sub>D1</sub>	28	61	–	Oscillation/internal logic system regulated voltage output pin
V <sub>C1</sub> –V <sub>C5</sub>	75–79	101–105	–	LCD system power supply pin 1/4 bias generated internally, 1/5 bias supplied externally (selected by mask option)
V <sub>REF</sub>	34	67	O	LCD system power supply testing pin
CA–CF	85–80	111–106	–	LCD system boosting/reducing capacitor connecting pin
OSC1	26	59	I	Crystal or CR oscillation input pin (selected by mask option)
OSC2	27	60	O	Crystal or CR oscillation output pin (selected by mask option)
OSC3	29	62	I	Ceramic or CR oscillation input pin (selected by mask option)
OSC4	30	63	O	Ceramic or CR oscillation output pin (selected by mask option)
K00–K03	70–67	99–96	I	Input port
K10, K11	66, 65	95, 94	I	Input port
K12	64	–	I	Input port
K13	63	93	I	Input port
P00–P03	62–59	92–89	I/O	I/O port
P10–P13	58–55	88–85	I/O	I/O port (switching to serial I/F input/output is possible by software)
P20	54	84	I/O	I/O port
P21	53	83	I/O	I/O port
P22	52	82	I/O	I/O port (switching to CL signal output is possible by software)
P23	51	81	I/O	I/O port (switching to FR signal output is possible by software)
R00	50	80	O	Output port
R01	49	79	O	Output port
R02	48	78	O	Output port (switching to TOUT signal output is possible by software)
R03	47	77	O	Output port (switching to FOUT signal output is possible by software)
R10–R13	46–43	76–73	O	Output port
R20–R23	42–39	72–69	O	Output port
COM0, COM1	23, 22	–	O	LCD common output pin (1/8, 1/16, 1/17 duty can be selected by software)
COM2–COM14	21, 20, 18–15, 86–92	56–51, 112–118		
COM15, COM16	93, 94	–		
SEG0–SEG59	14–1, 143–110, 106–95	50–1, 128–119	O	LCD segment output pin
BZ	24	57	O	Sound output pin
SVD	74	100	I	SVD external voltage input pin
RESET	32	65	I	Initial reset input pin
TEST	33	66	I	Testing input pin

**NOTICE**

No part of this material may be reproduced or duplicated in any form or by any means without the written permission of Seiko Epson. Seiko Epson reserves the right to make changes to this material without notice. Seiko Epson does not assume any liability of any kind arising out of any inaccuracies contained in this material or due to its application or use in any product or circuit and, further, there is no representation that this material is applicable to products requiring high level reliability, such as, medical products. Moreover, no license to any intellectual property rights is granted by implication or otherwise, and there is no representation or warranty that anything made in accordance with this material will be free from any patent or copyright infringement of a third party. This material or portions thereof may contain technology or the subject relating to strategic products under the control of the Foreign Exchange and Foreign Trade Control Law of Japan and may require an export license from the Ministry of International Trade and Industry or other approval from another government agency.

All product names mentioned herein are trademarks and/or registered trademarks of their respective companies.

©Seiko Epson Corporation 1998 All rights reserved.

**SEIKO EPSON CORPORATION****ELECTRONIC DEVICES MARKETING DIVISION****Electronic Device Marketing Department  
IC Marketing & Engineering Group**

421-8, Hino, Hino-shi, Tokyo 191-8501, JAPAN  
Phone: +81-(0)42-587-5816 Fax: +81-(0)42-587-5624

**ED International Marketing Department I (Europe & U.S.A.)**

421-8, Hino, Hino-shi, Tokyo 191-8501, JAPAN  
Phone: +81-(0)42-587-5812 Fax: +81-(0)42-587-5564

**ED International Marketing Department II (Asia)**

421-8, Hino, Hino-shi, Tokyo 191-8501, JAPAN  
Phone: +81-(0)42-587-5814 Fax: +81-(0)42-587-5110

Electric Device Information of EPSON WWW server

<http://www.epson.co.jp>

